



Project: Installation Gauddi software on LG webOS 3.0 monitorVersion: 2Date: 27-6-2017

Step 1: Setup your LG webOS scherm

If this is the first time you use the LG webOS monitor, you will need to carry out the following steps.

Turn on your monitor

- 1. To begin with the setup use the remote to turn on the LG monitor wait for it to fully power on.
 - a. After a few seconds you should see the Language Selection menu, go through this menu and press **OK**.
 - b. If your monitor doesn't boot to this menu you should perform a Factory Reset. How to do this, you can read in the tutorial: Factory Reset.
- 2. After Language and Country selection, you arrive in the Rotation Menu. If the monitor will be used in portrait mode, you can change OSD Portrait Mode. Please do not change Content Rotation. Press next.
- 3. Set your internet connection. It is preferable to use a wired connection. Press Connect.
- 4. **On/Off timer**: Please do not use this On/Off timer. You can manage the power on and power off in the Gauddi CMS. Press **Done**.
- **5.** Congratulations! Your LG webOS monitor is now ready for the Gauddi software. To do this please go to the next step.

	LANGUAGE & COUNTR Confirm your location and language settings	IT SELECTION	•	
	Language English			
	Continent North America		•	
	Country United States of America			
	Timezone Select			
0			•	
1 2 3 4 5 6	OK			
789				
0		U LA		
- A				
N OK P				





Project: Installation Gauddi software on LG webOS 3.0 monitorVersion: 2Date: 27-6-2017

Step 2: Installation Gauddi software on LG webOS monitor

Before installation of the Gauddi software you must have completed the first step (Setup your LG webOS monitor). Once you've done that you are ready to carry out the next step.

- 1. Press and hold the **Settings** button on the remote control until a small box with a chat bubble icon appears in the top-right corner.
- 2. Once you can see the chat bubble icon, please press quickly the following **8**, **0**, **8**, **0** and **OK** key sequence on your remote control, to open the **Server Settings** menu.
- 3. In the Server Settings menu, please set the following options:
 - a. Set the Application Launch Mode to Local.
 - b. Set the Fully Qualified Domain Name to On.
 - c. Set the URL to be: https://get.gauddi.com/lgapp/lgapp.zip
- 4. Next to the Local Application Upgrade option, please select the **Remote** option. and then confirm to begin the application install process on to your LG monitor.
- 5. Next to the Local Application Upgrade option, please select the **Remote** option. and then confirm to begin the application install process on to your LG monitor.
- 6. After a short time a message will appear on the monitor confirming that the Gauddi for LG webOS client installation has been successfully.
- 7. Please turn the monitor off and then (after 10 seconds) back on and Gauddi will start automatically after around 10 to 20 seconds.
- 8. The LG monitor will check if the correct firmware is installed. If not, it will ask to download and update the firmware. The firmware size is 450-600mb. The download time depends on your internet connection. Press **OK** to continue.
- 9. Congratulations! You have now successfully configured your LG monitor with Gauddi. You only need to connect your monitor with Gauddi CMS. To do this, please go to third and last step.







Project: Installation Gauddi software on LG webOS 3.0 monitorVersion: 2Date: 27-6-2017

Step 3: Connect your LG webOS monitor with the Gauddi license

Before you can connect to Gauddi CMS, you will need to carry out two previous steps: the first one is setup your LG webOS monitor and the second one is to install the Gauddi software on your monitor. Finally you connect your monitor to Gauddi CMS.

Open cms.gauddi.com (option 1)

- Prior to this installation you purchased a license from our webshop. If not, you can still do so through: <u>https://gauddi.nl/webshop/</u>
- 2. Open a browser on your phone or desktop computer and head to <u>cms.gauddi.com</u>. Login using your credentials.
- 3. Go to the top right corner and click **register player**. Enter the registration code, this is the 8 digit number on the LG monitor. Give your monitor a name.
- 4. Press register. Your monitor will automatically connect with the Gauddi cms.
- 5. You can start creating and scheduling professional-quality campaigns. Need help? Watch our <u>How-To-Video on how to create Campaigns & Playlists</u>.

Received a code from Gauddi (option 2)

- 1. Please make sure you see an 8 digit number on the LG monitor. Press **8**, **8**, **8**, **8** on the remote.
- 2. Now you can enter the code you have received from Gauddi. After entering, press **"OK"**. The system will confirm that the LG monitor is registered to the Gauddi CMS.
- 3. Open a browser on your phone or desktop computer and head to <u>cms.gauddi.com</u>. Login using your credentials.
- 4. You can start creating and scheduling professional-quality campaigns. Need help? Watch our <u>How-To-Video on how to create Campaigns & Playlists</u>.



