

Project : Installation Gaudi software on Philips D-line display
Version : 9
Date : 9-4-2018

Step 1: Setup your Philips Android D-line display

Check the serial number of the display

On the back of the display you can find the 'serial number' in the following format: AU3A***** (ex. AUG3A1723001510). When the number behind the stars is less than 1741000000, you cannot use this manual. The serial number in the given example is therefore not a match for this manual. You can find the right manual at support.gauddi.com, choose the manual **Installation Gaudi software on Philips D-line display with 'firmware update'** in the title.

Prepare USB

1. Go to <https://get.gauddi.com/philips/install/d-line.zip> and **download the file**.
2. Extract the files from the downloaded zip to the USB device (filesystem FAT, minimal 8GB).
3. Make sure the files are exported to the following path:
<usb drive>\philips\app\installer.apk
4. Optionally: add Android firmwares to <usb drive>\firmware\<version>.zip
5. Plug the USB stick into the Philips display.

Prepare Device

6. Pull out the **remote-control sensor** at the back of the display.
7. To begin with the setup, use the remote to turn on the Philips display wait for it to fully power on. If the device starts a wizard, you can continue to step 11.

Factory reset

8. Press **Home** and open **Configuration1**. Select **Factory Reset** and confirm the action.
9. Go to the Main Menu: press **Home** and immediately afterwards **1 8 8 8**.
10. Select **Settings** and after that **System Tools**; press **Factory Reset** and **Confirm** by choosing **Factory Reset** again. Choose **OK** to start the Factory Reset. The display will automatically turn off and reboot starting the reset sequence. After a few minutes, you'll end up in the 'Welcome' screen.

Device First Use

11. Language Settings Menu: select your preferred language and press **Start**.
12. Network type: **Select Ethernet** and press **Next** (It's preferable to use a wired connection).
13. Network settings: **Select DHCP** and press **Next**.
14. Signage display settings: **Import Signage Display Settings from USB** and press **Next**.
15. Clone media files into internal: **Press Skip**
16. Setup completed: **Press Finish**

Project : Installation Gaudi software on Philips D-line display
Version : 9
Date : 9-4-2018

Device Configuration

17. Go to the Main Menu: press **Home** and immediately afterwards **1 8 8 8**.
18. Open **Settings** and select **Date & Time**, then open **Select time zone** and **Select your current timezone** and press **OK**.
19. Go back to **Signage Display** in the left menu. Open **Custom App** and then **Select App**. Select **Gaudi** and press **Save**.
20. Press **Home** and navigate to **Configuration1**. In the right menu, open **Boot on source** and select input **Custom**.
21. Go to **Advanced option**, open **Power Save** and select **Mode1**.
22. Please turn the display off and then (after about 10 seconds) back on. The Gaudi installer will start automatically after around 10 to 20 seconds.

Gaudi Installer

23. Follow the instructions of the Gaudi installer. (Note: you can restart the installer at any time by pressing 'O' on the remote control)
24. When the installer instructs you to check the internet connection, either check your network cable or enable WIFI:
 - a. Go to the Main Menu: press **Home** and immediately afterwards **1 8 8 8**.
 - b. Open **Settings** and select **Wi-Fi**.
 - c. Select **Enable** and configure the desired network. Select the desired network and fill in the password.
 - d. Press the '**back**' button **three times** to return to the installer.

Check date/time

25. Open the menu by pressing **Home** and navigate to **Advanced option**. Open **Date & time** and check the date and time. If the date or time does not match, switch **Auto sync** off and on again.

USB-device

26. Do not remove the USB device from the display, it's needed for future updates.

Project : Installation Gaudi software on Philips D-line display
Version : 9
Date : 9-4-2018

Step 2: Connect your Philips display with the Gaudi license

Before you can connect to Gaudi CMS, you will need to carry out the two previous steps. Finally, you connect your display to Gaudi CMS. How to do this check out the two options.

Open cms.gaudi.com (option 1)

1. Open a browser on your phone or desktop computer and head to cms.gaudi.com. Login using your credentials.
2. Go to the top right corner and click register player. Enter the registration code, this is the 8-digit number on the Philips display. Give your display a name.
3. Press register. Your display will automatically connect with the Gaudi cms.
4. You can start creating and scheduling professional-quality campaigns. Need help? Watch our [How-To-Video on how to create Campaigns & Playlists](#).



Received a code from Gaudi (option 2)

1. Please make sure you see an 8-digit number on the Philips display. Press 8, 8, 8, 8 on the remote.
2. Now you can enter the code you have received from Gaudi. After entering, press “OK”. The system will confirm that the Philips display is registered to the Gaudi CMS.
3. Open a browser on your phone or desktop computer and head to cms.gaudi.com. Login using your credentials.
4. You can start creating and scheduling professional-quality campaigns. Need help? Watch our [How-To-Video on how to create Campaigns & Playlists](#).